

Bostonmatic Motor and Limit Switch Information

Hyperloop Motor (xyz)

Permanent Magnet DC Servo Motor

Torque: lb*in: 132 @ 0 RPM

Max Volts: 130

Max armature pulse amps: 210

Max RPM: 1100

K factor: 7.95

Model: A150

Part Num: 007-0150-001

Frame: 56-CM

Insulations: F

Totally enclosed non-vented

Tachometer: 31.5V/ 1000RPM

Spindle Motors

AC Induction Spindle Motors

MAX 7000 RPM

3HP

60Hz

230/460 VAC 3 Phase

7.5/3.8 AMP

Limit Switch

Class 9007

Serial: A

Type: B65A2SI

VAC: 120-160

Pilot Duty 720 VA 6A

Amps 10 10

Dynamic Research Corp

Wilmington Mass.

Model 39R-11-B13-625AA

S/N: 80104

Date: 6/84

Bostonmatic

Applied Electronics Inc.

Serial Num: MB11

Model: 14-40